



CLASS BOOSTER 350E



Input Voltage 1Ph 230 Volt
Battery 12 - 24 Volt, 30 > 400 Ah



Description

- Code: 353700

Battery chargers and starter

- Suitable for charging lead batteries: **WET** serviceable and maintenance free, **AGM**, **Start & Stop**
- Charging current regulation**
- Overload protection**
- Inversions of polarity protection**
- Short circuits protection**
- Manual charge breaker**

Features

Input Voltage (Volt 50-60Hz AC): 1 Ph x 230V

Nominal battery voltage (Volt): 12 / 24V

Power (KW): 1,1 / 5Kw

Average charging current (Amp): 20,0A

Effective charging current (Amp): 35,0A

Battery capacity (Ah min/max): 30 / 400Ah

Charging positions (N°): 4

Boosting Current (Amp 0 Volt CC): 300A 0V

Boosting current (Amp 1 Volt / EL): 220A 1V

Weight Kg \approx : 15.5

Dimension, Wid.-Dep.-Height (mm): 400 x 300 x 640

LOGISTIC INFO CODE : 353700

Barcode: 8011399011487

Package dimension, Wid.-Dep.-Height (mm): 595 x 310 x 265

Package weight kg: 18.1

Pieces for pallet: 24

HS code: 85044055

Optional accessory



FUSE 50 Amp

Ташев-Галвинг ООД
www.tashev-galving.com